



Letters on Applied and Pure Mathematics

Reconstructing the right-hand side of a Poisson equation with random noise

Yusuf Gurefe¹, Le Dinh Long ^{2,3*}

1. Department of Mathematics, Faculty of Science, Mersin University, Mersin, Turkey

2. Division of Applied Mathematics, Science and Technology Advanced Institute, Van Lang University, Ho Chi Minh City, Vietnam

3. Faculty of Applied Technology, School of Engineering, Van Lang University, Ho Chi Minh City, Vietnam

*Corresponding author

Abstract

An inverse source problem for the Poisson equation is looked at in this article. This is a problem that is poorly posed because even minor changes in the data can result in arbitrarily large changes in the results. We first demonstrate some useful lemmas about our proposed problem before presenting the main results. Then, at that point, we propose a regularization strategy to manage the reverse source issue and get a union rate with random noise.

Keywords: Conformable derivative, Fourier truncation method, Inverse source problem

2020 Mathematics Subject Classification: 35B65, 35K57, 35K99

Article history: Received 01 March 2023; Revised 15 April 2023; Accepted 01 May 2023; Online 08 May 2023

1 Introduction

Applications in science and engineering rely heavily on inverse source problems (see [1] and [2]). Finding the hidden source's location, size, and shape from the boundary's measured data is the inverse source problem of the Poisson equation's source term determination problem. The nonlinearity and illusory nature of this inverse source problem can be seen in the fact

that, even if a solution is found, it does not always rely on the measured data. The given data could have small errors that result in large errors in the solution. As a result, our proposed algorithms should make use of regularization methods. Numerous studies have been conducted on the Poisson equation's inverse source problems ([3], [4], [5], [9], [10], [11]). Bubnov, Erokhin and Isakov [5], [12] introduced a few hypothetical outcomes to recreate the obscure source or impediments from over determined limit estimations of arrangements of the Poisson condition. From over determined boundary measurements of Laplace equation solutions, the inverse problem of locating pointwise or small size conductivity defaults in a plane domain was solved by [4]. Hon and co. Several efficient numerical algorithms for resolving Poisson equation inverse source problems were proposed [11], [14]. In order to identify hidden obstacles, Hanke and Rundell's used the rational approximation method, see in [8]. Iterative algorithms exist to obtain source parameters from boundary measurement data [9], [10], [13], [15], [16]. An inverse potential problem for reconstructing an obstacle's shape was solved using iterative algorithms in Hettlich and Rundell's [10]. In this paper, assume that Ω is a simply connected bounded domain of \mathbb{R}^2 with a smooth boundary $\partial\Omega$, we consider to find a pair of functions $(u(x, y), \mathcal{F}(x))$ satisfying

$$-u_{xx} - u_{yy} = \mathcal{F}(x), 0 < x < \pi, \quad 0 < y < +\infty, \quad (1.1)$$

with boundary condition

$$u(0, y) = u(\pi, y) = 0, \quad 0 \leq y < +\infty, \quad (1.2)$$

and final condition

$$u(x, 1) = h(x), \quad 0 \leq x \leq \pi. \quad (1.3)$$

and

$$u(x, 0) = 0, \quad u(x, y)|_{y \rightarrow \infty} \text{ bounded}, \quad 0 \leq x \leq \pi, \quad (1.4)$$

where $u(x, 1) = h(x)$ is the supplementary condition and $\mathcal{F}(x)$ is the unknown source that is only dependent on one spatial variable. The inverse problem of identifying an unknown source is the name given to this issue. Numerous studies have been conducted on the various heat source types cited in the heat equation [17],[18],[19],[20],[21],[22]. We are aware of only a few papers that attempted to identify the random noise-based unknown source in the Poisson equation. Since we cannot anticipate that the measured data function $h_\epsilon(x)$ will decay at the same rate in $L^2(0, \pi)$, the problem (1.1) is ill-posed. The ill-posed problem will be addressed by means of the truncation regularization approach in the following section. The truncation regularization strategies have been read up for reverse issues, with the end goal that : Eldén can be found in [23], Xiong in [24], Fu in [25], and Qian in [26]. The model is random if the errors are brought on by unpredictability, such as wind, rain, humidity, or other factors. The approximate representation of the final data, h , is known as h_ϵ . The arbitrary model can't be tackled utilizing similar procedures used for the deterministic cases. It is regularly difficult to work out due to the irregular clamor. We have

$$\tilde{h}(x_k) = h(x_k) + \epsilon_k, \quad k = 1, \dots, n.$$

where $\epsilon_k, k = 1, \dots, n$ are unknown independent random errors because the function $h(x)$ in practical applications is the result of experimental observations and cannot be viewed without errors. As a matter of fact, these mistakes can emerge out of many sources like the estimating instrument or the climate. From now on, we put $x_k = \pi \frac{2k-1}{2n}$, with $k = 1, \dots, n$. We have a

data set $\mathcal{D} = (\tilde{h}(x_1), \tilde{h}(x_2), \dots, \tilde{h}(x_n))$, which is the measure of $(h(x_1), h(x_2), \dots, h(x_n))$, here \mathcal{D} satisfies

$$\tilde{h}(x_k) = h(x_k) + \sigma_k \varepsilon_k, \quad (1.5)$$

where, ε_k , $k = 1, \dots, n$ are unknown independent noises. Therefore, ε_k and σ_k are unknown positive constants that are constrained by the positive constant \mathcal{V}_{max} so that $0 \leq \sigma_k \leq \mathcal{V}_{max}$, respectively. The noises ε_k are independent of one another. There are no published results on the inverse source problem for fractional diffusion with random noise. Our fundamental issue in this paper is finding the source capability \mathcal{F} from the arbitrary information $h(x_k)$, $k = 1, \dots, n$. For $\sigma > 0$, let $\mathcal{H}^\sigma(\Omega)$ be the arrangement of all capabilities $\mathcal{F} \in L^2(\Omega)$ with

$$\|\mathcal{F}\|_{\mathcal{H}^\sigma(\Omega)}^2 = \sum_{p=1}^{\infty} p^{2\sigma} |\langle \mathcal{F}, \xi_p \rangle|^2 < \infty. \quad (1.6)$$

The outline of the paper is as follows. In Section 2, we present some preparatory knowledge. The main result is in Section 3.

2 Preliminaries

Lemma 2.1. (See in [7]) If $p \geq 1$, we have

$$(1 - \exp(-p))^{-1} \leq 2. \quad (2.1)$$

Lemma 2.2. Let $p = 1, \dots, n-1$, and $q = 1, 2, \dots$, with $x_k = \pi \frac{2k-1}{2n}$

and $\xi_p(x_k) = \sqrt{\frac{2}{\pi}} \sin(px_k)$, then we have

$$S_{p,q} = \frac{1}{n} \sum_{k=1}^n \xi_p(x_k) \xi_q(x_k) = \begin{cases} \frac{1}{\pi}, & q-p = 2\ell n \text{ or } q+p = 2\ell n (\ell \text{ even}), \\ -\frac{1}{\pi}, & q-p = 2\ell n \text{ or } q+p = 2\ell n (\ell \text{ odd}), \\ 0, & \text{otherwise.} \end{cases} \quad (2.2)$$

If $q = 1, 2, \dots, n-1$, then

$$S_{p,q} = \begin{cases} \frac{1}{\pi}, & p=q, \text{ and } \frac{1}{n} \sum_{k=1}^n \xi_p(x_k) = \begin{cases} 0, & p \neq 2\ell n, \\ (-1)^\ell \sqrt{\frac{2}{\pi}}, & p = 2\ell n. \end{cases} \end{cases} \quad (2.3)$$

Lemma 2.3. (See [6]) Let $p, n \in \mathbb{N}$ such that $1 \leq p \leq n-1$, and $h \in C[0, \pi]$. Then we have

$$\langle h, \xi_p \rangle = \frac{\pi}{n} \sum_{k=1}^n h(x_k) \xi_p(x_k) - \sum_{\ell=1}^{\infty} (-1)^\ell \left(\langle h, \xi_{p+2\ell n} \rangle + \langle h, \xi_{-p+2\ell n} \rangle \right), \quad 1 \leq p \leq n-1, \quad (2.4)$$

Lemma 2.4. Let $0 < \mathcal{M}_{tr} < n$, $\mathcal{M}_{tr} \in \mathbb{N}$, assume that h is as in Lemma 2.3, then the source function \mathcal{F} is given by

$$\begin{aligned} \mathcal{F}_{n, \mathcal{M}_{tr}}(x) &= \sum_{p=1}^{\mathcal{M}_{tr}} \frac{p^2}{1 - \exp(-p)} \left(\frac{\pi}{n} \sum_{k=1}^n h(x_k) \xi_p(x_k) \right. \\ &\quad \left. - \sum_{\ell=1}^{\infty} (-1)^\ell \left(\langle h, \xi_{p+2\ell n} \rangle + \langle h, \xi_{-p+2\ell n} \rangle \right) \right) \xi_p(x) \\ &\quad + \sum_{p=\mathcal{M}_{tr}+1}^{\infty} \frac{p^2}{1 - \exp(-p)} \langle h, \xi_p \rangle \xi_p(x). \end{aligned} \quad (2.5)$$

Proof The problem (1.1) has the mild solution:

$$u(x, y) = \sum_{p=1}^{\infty} \frac{1 - \exp(-py)}{p^2} \langle \mathcal{F}, \xi_p \rangle \xi_p, \text{ where } \left\{ \xi_p = \sqrt{\frac{2}{\pi}} \sin px, (p = 1, 2, \dots) \right\}, \quad (2.6)$$

and $\langle \mathcal{F}, \xi_p \rangle = \sqrt{\frac{2}{\pi}} \int_0^{\pi} \mathcal{F}(x) \sin(px) dx$. We have

$$h(x) = \sum_{p=1}^{\infty} \langle h, \xi_p \rangle \xi_p(x) = \sum_{p=1}^{\infty} \left(\frac{1 - \exp(-p)}{p^2} \right) \langle \mathcal{F}, \xi_p \rangle \xi_p(x). \quad (2.7)$$

Therefore, we have

$$\begin{aligned} \mathcal{F}(x) &= \sum_{p=1}^{\infty} \left(\frac{p^2}{1 - \exp(-p)} \right) \langle h, \xi_p \rangle \xi_p(x) \\ &= \sum_{p=1}^{\mathcal{M}_{tr}} \frac{p^2}{1 - \exp(-p)} \langle h, \xi_p \rangle \xi_p(x) + \sum_{p=\mathcal{M}_{tr}+1}^{\infty} \frac{p^2}{1 - e^{-p}} \langle h, \xi_p \rangle \xi_p(x) \\ &= \sum_{p=1}^{\mathcal{M}_{tr}} \frac{p^2}{1 - \exp(-p)} \left(\frac{\pi}{n} \sum_{k=1}^n h(x_k) \xi_p(x_k) - \sum_{\ell=1}^{\infty} (-1)^{\ell} \left(\langle h, \xi_{p+2\ell n} \rangle + \langle h, \xi_{-p+2\ell n} \rangle \right) \right) \xi_p(x) \\ &\quad + \sum_{p=\mathcal{M}_{tr}+1}^{\infty} \frac{p^2}{1 - \exp(-p)} \langle h, \xi_p \rangle \xi_p(x). \end{aligned} \quad (2.8)$$

3 The main results

Theorem 3.1. Let $\varepsilon > 0$ and $\varepsilon_k \sim N(0, 1)$ be independent normal random variables with $k = 1, \dots, n$ (as mentioned above), then a regularized function $\tilde{\mathcal{F}}_{n, \mathcal{M}_{tr}}$ for \mathcal{F} can be computed as follows

$$\tilde{\mathcal{F}}_{n, \mathcal{M}_{tr}}(x) = \sum_{p=1}^{\mathcal{M}_{tr}} \left(\frac{p^2}{1 - \exp(-p)} \right) \frac{\pi}{n} \sum_{k=1}^n h(x_k) \xi_p(x_k) \xi_p(x). \quad (3.1)$$

\mathcal{M}_{tr} is regularization parameters, it gives

$$\mathbb{E} \|\tilde{\mathcal{F}}_{n, \mathcal{M}_{tr}} - \mathcal{F}\|_{L^2(\Omega)}^2 \leq 2(\mathcal{M}_{tr})^{-2\sigma} E^2 + 8\mathcal{M}_{tr}^4 \left(\frac{\pi^2}{n^2} \right) \nu_{\max}^2 + \frac{\pi^4}{144} \frac{\|\mathcal{F}\|_{L^2(\Omega)}^2}{n^4}. \quad (3.2)$$

Let $\mathcal{M}_{tr} = \mathcal{M}_{tr, n}$ such that $0 < \mathcal{M}_{tr} = \mathcal{M}_{tr, n} < n$ and

$$\lim_{n \rightarrow +\infty} \frac{\mathcal{M}_{tr}^4}{n} = 0, \quad (3.3)$$

then

$$\mathbb{E} \|\tilde{\mathcal{F}}_{n, \mathcal{M}_{tr}} - \mathcal{F}\|_{L^2(\Omega)}^2 \text{ is of order } \left\{ \frac{\mathcal{M}_{tr}^4}{n}, (\mathcal{M}_{tr})^{-2\sigma} \right\}. \quad (3.4)$$

Remark 3.2. If we choose $\mathcal{M}_{tr} = n^{\frac{1}{4+2\sigma}}$, with (3.4), then we have

$$\mathbb{E} \|\tilde{\mathcal{F}}_{n, \mathcal{M}_{tr}} - \mathcal{F}\|_{L^2(\Omega)}^2 \text{ is of order } n^{-\frac{\sigma}{2+2\sigma}}. \quad (3.5)$$

Proof:

Using the inequality $1 - \exp(-p) \leq p$, $\forall p > 0$, we receive

$$|\langle h, \xi_p \rangle| = \left(\frac{1 - \exp(-p)}{p^2} \right) |\langle \mathcal{F}, \xi_p \rangle| \leq \frac{\|\mathcal{F}\|_{L^2(\Omega)}}{p}. \quad (3.6)$$

Using (2.8) and (3.1), we obtain

$$\begin{aligned} & \tilde{\mathcal{F}}_{n, \mathcal{M}_{tr}}(x) - \mathcal{F}(x) \\ &= \sum_{p=1}^{\mathcal{M}_{tr}} \left(\frac{p^2}{1 - \exp(-p)} \right) \left(\frac{\pi}{n} \sum_{k=1}^n \sigma_k \varepsilon_k \xi_p(x_k) + \sum_{\ell=1}^{\infty} (-1)^\ell \left(\langle h, \xi_{p+2\ell n} \rangle + \langle h, \xi_{-p+2\ell n} \rangle \right) \right) \xi_p(x) \\ & - \sum_{p=\mathcal{M}_{tr}+1}^{\infty} \left(\frac{p^2}{1 - \exp(-p)} \right) \langle h, \xi_p \rangle \xi_p(x). \end{aligned} \quad (3.7)$$

Applying Lemma 2.4, we have

$$\begin{aligned} & \|\tilde{\mathcal{F}}_{n, \mathcal{M}_{tr}} - \mathcal{F}\|_{L^2(\Omega)}^2 \\ &= \sum_{p=1}^{\mathcal{M}_{tr}} \left(\frac{p^2}{1 - \exp(-p)} \right)^2 \left(\frac{\pi}{n} \sum_{k=1}^n \sigma_k \varepsilon_k \xi_p(x_k) + \sum_{\ell=1}^{\infty} (-1)^\ell \left(\langle h, \xi_{p+2\ell n} \rangle + \langle h, \xi_{-p+2\ell n} \rangle \right) \right)^2 \\ & + \sum_{p=\mathcal{M}_{tr}+1}^{\infty} \left(\frac{p^2}{1 - \exp(-p)} \right)^2 |\langle g, \xi_p \rangle|^2. \end{aligned} \quad (3.8)$$

The fact that $\mathbb{E}(\varepsilon_j \varepsilon_l) = 0$; ($j \neq l$), and $\mathbb{E} \varepsilon_j = 0$; $j = 1, 2, \dots, n$. One has

$$\begin{aligned} & \mathbb{E} \|\tilde{\mathcal{F}}_{n, \mathcal{M}_{tr}} - \mathcal{F}\|_{L^2(\Omega)}^2 \\ & \leq 2 \underbrace{\sum_{p=\mathcal{M}_{tr}+1}^{\infty} \left(\frac{p^2}{1 - \exp(-p)} \right)^2 |\langle g, \xi_p \rangle|^2}_{\mathcal{J}_1} \\ & + 2 \underbrace{\sum_{p=1}^{\mathcal{M}_{tr}} \left(\frac{p^2}{1 - \exp(-p)} \right)^2 \left(\frac{\pi^2}{n^2} \sum_{k=1}^n \sigma_k^2 \mathbb{E} \varepsilon_k^2 + \underbrace{\left(\sum_{\ell=1}^{\infty} (-1)^\ell \left(\langle h, \xi_{p+2\ell n} \rangle + \langle h, \xi_{-p+2\ell n} \rangle \right) \right)^2}_{\mathcal{J}_2} \right)}_{\mathcal{J}_3}. \end{aligned} \quad (3.9)$$

We know that $\sum_{\ell=1}^{\infty} \frac{1}{\ell^2} = \frac{\pi^2}{6}$, we obtain

$$\begin{aligned} \mathcal{J}_2 & \leq \sum_{l=1}^{\infty} |\langle h, \xi_{p+2\ell n} \rangle + \langle h, \xi_{-p+2\ell n} \rangle| \\ & \leq \frac{\|\mathcal{F}\|_{L^2(\Omega)}}{n^2} \left[\sum_{\ell=1}^{\infty} \frac{1}{(p+2\ell n)^2} + \sum_{\ell=1}^{\infty} \frac{1}{(-p+2\ell n)^2} \right] \leq \frac{\pi^2}{12} \frac{\|\mathcal{F}\|_{L^2(\Omega)}}{n^2}. \end{aligned} \quad (3.10)$$

For $p \geq 1$, $1 = p^{2\sigma} p^{-2\sigma}$, we can rewrite \mathcal{J}_1 as follows

$$\mathcal{J}_1^2 = \sum_{p=\mathcal{M}_{tr}+1}^{\infty} \left(\frac{p^2}{1 - \exp(-p)} \right)^2 |\langle h, \xi_p \rangle|^2 = \sum_{p=\mathcal{M}_{tr}+1}^{\infty} p^{2\sigma} p^{-2\sigma} |\langle \mathcal{F}, \xi_p \rangle|^2, \quad (3.11)$$

this leads to

$$\mathcal{J}_1^2 \leq (\mathcal{M}_{tr})^{-2\sigma} E^2. \quad (3.12)$$

Next, \mathcal{J}_3 can be bounded as follows

$$\mathcal{J}_3^2 \leq \sum_{p=1}^{\mathcal{M}_{tr}} \left(\frac{p^2}{1 - e^{-p}} \right)^2 \left(\frac{\pi^2}{n^2} \sum_{k=1}^n \sigma_k^2 \mathbb{E} \epsilon_k^2 + \mathcal{J}_2^2 \right)^2. \quad (3.13)$$

Since $\sigma_k \leq \mathcal{V}_{\max}$, using the Lemma 2.1, one has

$$\mathcal{J}_2^2 \leq \sum_{p=1}^{\mathcal{M}_{tr}} 4p^4 \left(\frac{\pi^2}{n^2} \mathcal{V}_{\max}^2 + \frac{\pi^4}{144} \frac{\|f\|_{L^2(\Omega)}^2}{n^4} \right) \leq 4\mathcal{M}_{tr}^4 \left(\frac{\pi^2}{n^2} \mathcal{V}_{\max}^2 + \frac{\pi^4}{144} \frac{\|\mathcal{F}\|_{L^2(\Omega)}^2}{n^4} \right). \quad (3.14)$$

Combining (3.9), (3.12), and (3.13), we obtain

$$\mathbb{E} \|\tilde{\mathcal{F}}_{n, \mathcal{M}_{tr}} - \mathcal{F}\|_{L^2(\Omega)}^2 \leq 2(\mathcal{M}_{tr})^{-2\sigma} E^2 + 8\mathcal{M}_{tr}^4 \left(\frac{\pi^2}{n^2} \mathcal{V}_{\max}^2 + \frac{\pi^4}{144} \frac{\|\mathcal{F}\|_{L^2(\Omega)}^2}{n^4} \right). \quad (3.15)$$

This completes the proof.

Acknowledgments

Le Dinh Long is supported by Van Lang University.

Authors Contributions

All authors read and approved the final version of the manuscript.

Competing Interests

The authors declare that they have no known competing financial interests or personal relationships that could have appeared to influence the work reported in this paper.

References

- [1] M. Cheney, D. Isaacson, J. C. Newell; *Electrical impedance tomography*, SIAM review (1999), 85–101.
- [2] M. Hämäläinen, R. Hari, R. J. Ilmoniemi, J. Knuutila, O. V. Lounasmaa; *Magnetoencephalography theory, instrumentation, and applications to noninvasive studies of the working human brain*, Reviews of Modern Physics **65** (1993), 413–497.
- [3] A. E. Badiya, T. Ha-Duong; *An inverse source problem in potential analysis*, Inverse Problems, **16** (2000), 651.
- [4] L. Baratchart, A. B. Abda, F. B. Hassen, J. Leblond; *Recovery of pointwise sources or small inclusions in 2D domains and rational approximation*, Inverse problems **21** (2005), no. 1, 51.
- [5] B. A. Bubnov, G. N. Erokhin; *Inverse and ill-posed sources problems*, vol. 9, Vsp, 1997.
- [6] Nguyen Huy Tuan, Erkan Nane, *Inverse source problem for time-fractional diffusion with discrete random noise*, Statistics and Probability Letters, (2016), <http://dx.doi.org/10.1016/j.spl.2016.09.026>.
- [7] Fan Yang, *The truncation method for identifying an unknown source in the Poisson equation*,
- [8] M. Hanke, W. Rundell; *On rational approximation methods for inverse source problems*, Inverse Problems and Imaging **5** (2011), no. 1, 185–202.
- [9] B. He, T. Musha, Y. Okamoto, S. Homma, Y. Nakajima, T. Sato; *Electric dipole tracing in the brain by means of the boundary element method and its accuracy*, Biomedical Engineering, IEEE Transactions on BME-34 (1987), no. 6, 406–414.

- [10] F. Hettlich, W. Rundell; *Iterative methods for the reconstruction of an inverse potential problem*, Inverse problems **12** (1999), no. 3, 251.
- [11] Y. C. Hon, M. Li, Y.A. Melnikov; *Inverse source identification by Green's function*, Engineering Analysis with Boundary Elements **34** (2010), no. 4, 352–358.
- [12] V. Isakov; *Inverse source problems*, no. 34, American Mathematical Soc., 1990.
- [13] R. N. Kavanagh, T. M. Darcey, D. Lehmann, D. H. Fender; *Evaluation of methods for three dimensional localization of electrical sources in the human brain*, Biomedical Engineering, IEEE Transactions on BME-25 (1978), no. 5, 421–429.
- [14] L. Ling, Y.C. Hon, M. Yamamoto; *Inverse source identification for poisson equation*, Inverse problems in science and engineering **13** (2005), no. 4, 433–447.
- [15] J. Nenonen, T. Katila, M. Leinio, J. Montonen, M. Makijarvi, P. Siltanen; *Magnetocardiographic functional localization using current multipole models*, Biomedical Engineering, IEEE Transactions on **38** (1991), no. 7, 648–657.
- [16] K. Ohnaka, K. Uosaki; *Boundary element approach for identification of point forces of distributed parameter systems*, International Journal of Control **49** (1989), no. 1, 119–127.
- [17] J.R. Cannon, P. Duchateau, *Structural identification of an unknown source term in a heat equation*, Inverse Probl. **14** (1998) 535 – 551.
- [18] G.S. Li, *Data compatibility and conditional stability for an inverse source problem in the heat equation*, Appl. Math. Comput. **173** (2006) 566-581.
- [19] Z. Yi, D.A. Murio, *Source term identification in 1-D IHCP*, Comput. Math. Appl. **47** (2004) 1921-1933.
- [20] L. Yan, F.L. Yang, C.L. Fu, *A meshless method for solving an inverse spacewise-dependent heat source problem*, J. Comput. Phys. **228** (2009) 123-136.
- [21] A. Farcas, D. Lesnic, *The boundary-element method for the determination of a heat source dependent on one variable*, J. Eng. Math. **54** (2006) 375 – 388.
- [22] L. Yan, C.L. Fu, F.L. Yang, *The method of fundamental solutions for the inverse heat source problem*, Eng. Anal. Bound. Elem. **32** (2008) 216 – 222.
- [23] L. Elden, F. Berntsson, T. Reginska, *Wavelet and Fourier methods for solving the sideways heat equation*, SIAM J. Sci. Comput. **21** (6) (2000) 2187 – 2205.
- [24] X.T. Xiong, C.L. Fu, H.F. Li, *Fourier regularization method of a sideways heat equation for determining surface heat flux*, J. Math. Anal. Appl. **317** (2006) 331 – 348.
- [25] C.L. Fu, X.T. Xiong, Z. Qian, *Fourier regularization for a backward heat equation*, J. Math. Anal. Appl. **331** (2007) 472-480.
- [26] Z. Qian, C.L. Fu, X.T. Xiong, T. Wei, *Fourier truncation method for high order numerical derivatives*, Appl. Math. Comput. **181** (2006) 940-948.